

CLAIMS

1 1. A method of demodulating a received signal corresponding to a plurality
2 of transmitted symbol sequences originating from both a first user and a second
3 user, the method comprising:

4 initializing a first-user symbol sequence corresponding to the first
5 user and a second-user symbol sequence corresponding to the second
6 user and channel estimates for the first user and the second user; and

7 jointly detecting the first-user symbol sequence and the second-user
8 symbol sequence using, at each of a plurality of iterations previous first and
9 second user symbol sequences and the channel estimates for the first user
10 and the second user, and based on the use of transmit diversity by at least
11 one of the first user and the second user.

1 2. The method of claim 1 further comprising updating the channel
2 estimates prior to each of the plurality of iterations.

1 3. The method of claim 1 wherein channel estimates are obtained using
2 alternate pilot channels in a code division multiplexed access (CDMA) system.

1 4. The method of claim 1 wherein initializing is accomplished by a semi-
2 blind initialization procedure.

1 5. The method of claim 2 wherein initializing is accomplished by a semi-
2 blind initialization procedure.

1 6. The method of claim 3 wherein initializing is accomplished by a semi-
2 blind initialization procedure.

1 7. A method of demodulating a received signal corresponding to a plurality
2 of transmitted symbols originating from both a first user and a second user, the
3 method comprising:

4 initializing a first-user symbol corresponding to the first user and a
5 second-user symbol corresponding to the second user and channel
6 estimates for the first user and the second user;

7 jointly detecting a first-user symbol and a second-user symbol at a
8 current symbol time using previous first and second user symbols and
9 channel estimates for the first user and the second user, and based on the
10 use of transmit diversity by at least one of the first user and the second
11 user; and

12 if additional symbol times remain, jointly detecting the first user
13 symbol and the second user symbol at a next symbol time.

1 8. The method of claim 7 further comprising:
 2 predicting the channel estimates for a next symbol time, at least in
 3 part through the use of channel tracking; and
 4 updating the first-user symbol and the second-user symbol.

1 9. The method of claim 7 wherein the signals from the first user and the
 2 second user are asynchronous, and wherein:
 3 the initialization further comprises the initialization of a pulse-shape
 4 component; and
 5 the jointly detecting is accomplished at least in part through
 6 reference to the pulse-shape component.

1 10. The method of claim 8 wherein the signals from the first user and the
 2 second user are asynchronous, and wherein:
 3 the initialization further comprises the initialization of a pulse-shape
 4 component; and
 5 the jointly detecting is accomplished at least in part through
 6 reference to the pulse-shape component.

1 11. Apparatus for demodulating a received signal corresponding to a
2 plurality of transmitted symbol sequences originating from both a first user and a
3 second user, the apparatus comprising:
4 means for initializing a first-user symbol sequence corresponding to
5 the first user and a second-user symbol sequence corresponding to the
6 second user;
7 means for initializing channel estimates for the first user and the
8 second user; and
9 means for iteratively and jointly detecting the first-user symbol
10 sequence and the second-user symbol sequence using previous first and
11 second user symbol sequences and the channel estimates for the first user
12 and the second user, and based on the use of transmit diversity by at least
13 one of the first user and the second user.

1 12. Apparatus for demodulating a received signal corresponding to a
2 plurality of transmitted symbols originating from both a first user and a second
3 user, the apparatus comprising:
4 means for initializing a first-user symbol corresponding to the first
5 user and a second-user symbol corresponding to the second user;
6 means for initializing channel estimates for the first user and the
7 second user; and
8 means for jointly and recursively detecting a first-user symbol and a
9 second-user symbol at specific symbol times using previous first and

10 second user symbols and channel estimates for the first user and the
11 second user, and based on the use of transmit diversity by at least one of
12 the first user and the second user.

1 13. A receiving system operable to demodulate a received signal
2 corresponding to a plurality of transmitted symbol sequences originating from both
3 a first user and a second user, the system comprising:

4 a channel estimation unit operable to produce channel estimates for
5 the first user and the second user; and

6 a detector unit operatively connected to the channel estimation unit,
7 the detector unit operable to jointly detect a first-user symbol sequence and
8 a second-user symbol sequence using previous first and second user
9 symbol sequences and the channel estimates for the first user and the
10 second user, and based on the use of transmit diversity by at least one of
11 the first user and the second user.

1 14. The system of claim 13 wherein the channel estimation unit updates
2 the channel estimates prior to each of a plurality of iterations.

1 15. The system of claim 13 wherein the channel estimation unit obtains
2 channel estimates using alternate pilot channels in a code division multiplexed
3 access (CDMA) system.

1 16. The system of claim 13 further comprising semi-blind initialization logic
2 operatively connected to the channel estimation unit and the detector unit.

1 17. The system of claim 14 further comprising semi-blind initialization logic
2 operatively connected to the channel estimation unit and the detector unit.

1 18. The system of claim 15 further comprising semi-blind initialization logic
2 operatively connected to the channel estimation unit and the detector unit.

1 19. A receiving system operable to demodulate a received signal
2 corresponding to a plurality of transmitted symbols originating from both a first
3 user and a second user, the system comprising:

4 a channel estimation unit operable to produce channel estimates for
5 the first user and the second user; and

6 a detector unit operatively connected to the channel estimation unit,
7 the detector unit operable to jointly detect a first-user symbol and a second-

8 user symbol at specific symbol times using previous first and second user
9 symbols and the channel estimates for the first user and the second user,
10 and based on the use of transmit diversity by at least one of the first user
11 and the second user.

1 20. The system of claim 19 wherein the detector unit further comprises a
2 symbol update unit and the symbol update unit and the channel estimation unit
3 each further comprise:

4 reformulation operators;
5 conjugation operators connected to the reformulation operators; and
6 multipliers and adders interconnected with the reformulation
7 operators and conjugation operators.

1 21. The system of claim 19 wherein the channel estimation logic predicts
2 channel estimates at least in part through channel tracking.

1 22. The system of claim 20 wherein the channel estimation logic predicts
2 channel estimates at least in part through channel tracking.

1 23. The system of claim 19 wherein the detector unit is further operable to
2 detect asynchronous signals through reference to a pulse shape component.

1 24. The system of claim 20 wherein the detector unit is further operable to
2 detect asynchronous signals through reference to a pulse shape component.

1 25. The system of claim 21 wherein the detector unit is further operable to
2 detect asynchronous signals through reference to a pulse shape component.

1 26. The system of claim 22 wherein the detector unit is further operable to
2 detect asynchronous signals through reference to a pulse shape component.

1 27. A mobile terminal comprising:
2 a processor system for controlling the operation of the mobile
3 terminal;
4 a radio block operable to transmit signals, and also to receive
5 signals corresponding to a plurality of transmitted symbols originating from
6 both a first user and a second user;
7 baseband logic operatively connected to the radio block and the
8 processor system, the baseband logic further comprising a channel

9 estimation unit operable to produce channel estimates for the first user and
10 the second user, and a detector unit operatively connected to the channel
11 estimation unit, the detector unit operable to jointly detect first-user symbols
12 and second-user symbols based on the channel estimates for the first user
13 and the second user and based on the use of transmit diversity by at least
14 one of the first user and the second user.

1 28. The mobile terminal of claim 27 wherein the channel estimation unit
2 performs block estimation and the detector unit performs block detection of the
3 first user symbols and the second user symbols.

1 29. The mobile terminal of claim 27 wherein the channel estimation unit
2 performs recursive estimation using channel tracking and the detector unit
3 performs recursive detection of the first user symbols and the second user
4 symbols.

1 30. The mobile terminal of claim 29 wherein the signals corresponding to
2 the plurality of transmitted symbols originating from both the first user and the
3 second user can be asynchronous, and further wherein the detector unit operates
4 with reference to a pulse shape-shape component.

1 31. The mobile terminal of claim 27 wherein the channel estimation unit
2 produces channel estimates by referring to alternate pilot channels in a code
3 division multiplexed access (CDMA) system.

1 32. The mobile terminal of claim 27 wherein the detector unit further
2 comprises a symbol update unit, and the symbol update unit and the channel
3 estimation unit each further comprise:
4 reformulation operators;
5 conjugation operators connected to the reformulation operators; and
6 multipliers and adders interconnected with the reformulation
7 operators and conjugation operators.

1 33. The mobile terminal of claim 29 wherein the detector unit further
2 comprises a symbol update unit, and the symbol update unit and the channel
3 estimation unit each further comprise:
4 reformulation operators;
5 conjugation operators connected to the reformulation operators; and
6 multipliers and adders interconnected with the reformulation
7 operators and conjugation operators.

1 34. The mobile terminal of claim 30 wherein the detector unit further
2 comprises a symbol update unit, and the symbol update unit and the channel
3 estimation unit each further comprise:
4 reformulation operators;
5 conjugation operators connected to the reformulation operators; and
6 multipliers and adders interconnected with the reformulation
7 operators and conjugation operators.

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000